

**IN THE CLAIMS:**

Amend claims 17 and 22 as shown in the following listing of claims, which replaces all previous listings and versions of claims.

1. (previously presented) A magnetic bearing device, comprising:

a rotor:

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets:

switch means for switching a voltage of the common node; and

excitation control means for controlling excitation of each of the electromagnets by a supply current supplied from the other end of one of the electromagnets to a negative electrode of the power source, or by a regenerated current regenerated from the other end of one of the electromagnets to a positive electrode of the power source; wherein

the switch means includes:

a first switch element for connecting and disconnecting between the positive electrode and the common node; and

a first rectifier element for causing a current to flow from the negative electrode to the common node; and

the excitation control means includes:

a second switch element for connecting and disconnecting between the other end of one of the electromagnets and the negative electrode; and

a second rectifier element for causing a current to flow from the other end of one of the electromagnets to the positive electrode.

2. (withdrawn) A magnetic bearing device, comprising:

a rotor;

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets;

switch means for switching a voltage of the common node; and

excitation control means for controlling excitation of each of the electromagnets by a supply current supplied

from a positive electrode of the power source to the other end of one of the electromagnets, or by a regenerated current regenerated from a negative electrode of the power source to the other end of one of the electromagnets; wherein

the switch means includes:

a first switch element for connecting and disconnecting between the common node and the negative electrode; and

a first rectifier element for causing a current to flow from the common node to the positive electrode; and

the excitation control means includes:

a second switch element for connecting and disconnecting between the positive electrode and the other end of one of the electromagnets; and

a second rectifier element for causing a current to flow from the negative electrode to the other end of one of the electromagnets.

3.-4. (canceled)

5. (withdrawn) A magnetic bearing device, comprising:

a rotor;

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets;

switch means for switching a voltage of the common node;

a first excitation control means for controlling excitation of at least one of the plurality of electromagnets by a supply current supplied from the other end of one of the electromagnets to a negative electrode of the power source, or by a regenerated current regenerated from the other end of one of the electromagnets to a positive electrode of the power source; and

a second excitation control means for controlling excitation of electromagnets other than the at least one electromagnet controlled through excitation by the first excitation control means, by a supply current supplied from the positive electrode to the other end of another one of the electromagnets, or by a regenerated current regenerated from the negative electrode to the other end of the another one of the electromagnets; wherein

the switch means includes:

a switch element for connecting and disconnecting between the common node and the negative electrode, and a switch element for connecting and disconnecting between the positive electrode and the common node; and

a rectifier element for causing a current to flow from the common node to the positive electrode, and causing a current to flow from the negative electrode to the common node, respectively;

the first excitation control means includes:

a switch element for connecting and disconnecting between the other end of one of the electromagnets and the negative electrode; and

a rectifier element for causing a current to flow from the other end of the one of the electromagnets to the positive electrode; and

the second excitation control means includes:

a switch element for connecting and disconnecting between the positive electrode and the other end of another one of the electromagnets; and

a rectifier element for causing a current from the negative electrode to the other end of the another one of the electromagnets.

6. (withdrawn) The magnetic bearing device according to claim 5, characterized in that the current caused to flow through each of the electromagnets is increased, decreased, or maintained to be constant by adjusting a switching phase of the switch means and control phases of the first excitation control means and the second excitation control means within a common control cycle.

7.-11. (canceled)

12. (previously presented) The magnetic bearing device according to claim 1, wherein the current caused to flow through each of the electromagnets is increased, decreased, or maintained to be constant by adjusting a switching phase of the switch means and a control phase of the excitation control means within a common control cycle.

13. (previously presented) The magnetic bearing device according to claim 1, wherein the first rectifier element includes a third switch element connected in parallel therewith.

14. (withdrawn) The magnetic bearing device according to claim 2, wherein the current caused to flow through each of the electromagnets is increased, decreased, or maintained to be constant by adjusting a switching phase of the switch means and a control phase of the excitation control means within a common control cycle.

15. (withdrawn) The magnet bearing device according to claim 2, wherein the first rectifier element includes a third switch element connected in parallel therewith.

16. (withdrawn) The magnetic bearing device according to claim 5, wherein the plurality of electromagnets are constituted by being divided into two groups, one group controlled by the first excitation control means and the other

group controlled by the second excitation control means so that the current caused to flow between the positive electrode and the common node and the current caused to flow between the common node and the negative electrode are made substantially equalized.

17. (currently amended) The magnetic bearing device according to ~~claim 5~~ claim 1, further comprising current detecting means for detecting a value of the current when a constant current is caused to flow through the electromagnets.

18. (previously presented) The magnetic bearing device according to claim 17, wherein the current detecting means includes a resistance having one end connected to the negative electrode, and a detection portion for detecting a current flowing through the resistance.

19. (withdrawn) The magnetic bearing device according to claim 6, wherein the plurality of electromagnets are constituted by being divided into two groups, one group controlled by the first excitation control means and the other group controlled by the second excitation control means so that the current caused to flow between the positive electrode and the common node and the current caused to flow between the common node and the negative electrode are made substantially equalized.

20. (withdrawn) The magnetic bearing device according to claim 6, further comprising current detecting means for

detecting a value of the current when a constant current is caused to flow through the electromagnets.

21. (withdrawn) A turbo molecular pump comprising the magnetic bearing device according to claim 6 mounted thereto, wherein the rotor has rotary vanes and a rotor shaft placed at the center of the rotary vanes; and each of the electromagnets levitates the rotor shaft by a magnetic force.

22. (currently amended) A turbo molecular pump comprising the magnetic bearing device according to ~~claim 5~~ claim 1 mounted thereto, wherein the rotor has rotary vanes and a rotor shaft placed at the center of the rotary vanes; and each of the electromagnets levitates the rotor shaft by a magnetic force.

23. (withdrawn) A turbo molecular pump comprising the magnetic bearing device according to claim 2 mounted thereto, wherein the rotor has rotary vanes and a rotor shaft placed at the center of the rotary vanes; and each of the electromagnets levitates the rotor shaft by a magnetic force.

24. (previously presented) A turbo molecular pump comprising the magnetic bearing device according to claim 1 mounted thereto, wherein the rotor has rotary vanes and a rotor shaft placed at the center of the rotary vanes; and each of the electromagnets levitates the rotor shaft by a magnetic force.